



BC0807F USB Battery Charger can independently charge 1 to 4 pcs of rechargeable batteries independently. With the LED Charging Indicators, the charger will provide different signals so that you will notice when the batteries are fully charged.

#### Main Features

- 4 Independent Charging Channels
- Easy to Monitor LED Charge Indicators

Red	Charging
Flashing	Defective or non-rechargeable batteries / short circuit
Green	Fully charged / trickle

- 6 Level Charge Protections:
  - ΔV cut off
  - Timer Control Protection
  - Reverse Polarity Protection
  - Over Current Protection
  - Over Temperature Protection
  - Defective and Non-rechargeable battery detection

#### Specifications

Input: 5V  $\square$  2A  
 Output: AA: 1600mA (1-2pcs)  
 800mA (3-4pcs)  
 AAA: 800mA (1-2pcs)  
 400mA (3-4pcs)

#### Colors

Black

#### Appr. Charging Time\*

Type of Battery	Charging time(Appr.)	
	1-2 Cells	3-4 Cells
Ni-MH AA 2700mAh	2h	4h
Ni-MH AA 2000mAh	1.5h	3h
Ni-MH AAA 1100mAh	1.5h	3h
Ni-MH AAA 800mAh	70min	2.5h
Ni-Cd AA 1000mAh	45min	2.5h
Ni-Cd AAA 300mAh	30min	1h

\*The charging time varies according to different batteries. For a more complete listing please visit [www.camelionbattery.com](http://www.camelionbattery.com)

#### Package Details



BC-0807F

#### Accessory:



Micro USB Cable (L:50CM)

#### Related Products

##### BC-0805A



Mini USB Battery Charger

##### BC-0805B



Mini USB Battery Charger

##### LBC-313



Universal Battery Charger

##### LBC-312



Universal Battery Charger

BC-0807F Camelion ©2017 All Rights Reserved. All other brand names are trademarks or registered trademarks of the respective companies. Contents do not constitute a warranty.

## Available Now

Contact us: [info@camelionbattery.com](mailto:info@camelionbattery.com)  
[www.camelionbattery.com](http://www.camelionbattery.com)

Pictures are for illustrative purposes only and may differ slightly from the actual product. Camelion Product development may require changes without notice.